



Sound Surveillance™

Electronic Technical Services Inc.
211 Conchas SE
Albuquerque, NM 87123
PH 505-888-3923 FAX 505-888-3926
Website: www.etsnm.com

SMM2 2 Channel Microphone Mixer

Description

Powers and mixes the audio of 2 Sound Surveillance™ microphones into one un-balanced line level RCA (or 3.5mm) output. Use to expand the coverage of one zone using up to 2 microphones or monitor up to 2 separate zones mixed together.



Includes

- SMM2 Microphone Mixer.
- 12 VDC AC adapter.
- 1 each 3' RCA or 3.5mm patch cable.
- Installation instructions.

Options

- SPECIFY: RCA OR 3.5mm output connector.

Wiring Requirements

- Microphone cable runs: Stranded 22-gauge, 2-conductor shielded cable. Distances up to 1500 feet each.

Warranty : 1 year parts and labor.

Made in USA

SMM2 Microphone Mixer Specifications

- Standard RCA or 3.5mm jack for connection to DVRs etc.
- Line level (0db) output level.
- Euro-style connectors makes cable terminations fast and clean.
- Separate volume control for each microphone.
- LED power indicator.
- Power: 12 VDC @ 20mA
- Reverse polarity protected.
- All power circuitry and cable runs protected with auto-reset type fuse.
- Black plastic ABS housing.
- Dimensions: L 3.3 x W 2.0 x H 1.6

Caution

It is the responsibility of the installation company and end user to comply with state and federal privacy laws regarding the use of audio surveillance equipment. If you are unfamiliar with these laws, consult a qualified attorney. In most cases, posting the provided warning labels in plain view is all that is required.