



Electronic Technical Services Inc.
211 Conchas SE
Albuquerque, NM 87123
PH 505-888-3923 FAX 505-888-3926

Sound Surveillance™

SMM-4 4 Channel Microphone Mixer

Description

Powers and mixes the audio of up to 4 Sound Surveillance™ SM1 series microphones into one un-balanced line level RCA output. Use to expand the coverage of one zone using up to 4 microphones or monitor up to 4 separate zones mixed together.



Includes

- SMM-4 Microphone Mixer.
- 15 VDC 800ma AC adapter.
- 1 each 6' RCA patch cord.
- Installation instructions.

Options

- Add -3.5MM or -FL (Flying Leads) to P/N for alternate output cables.

Wiring Requirements

- Microphone cable runs: Stranded 22-gauge, 2-conductor shielded cable. Distances up to 1000 feet each.

SMM-4 Microphone Mixer Specifications

- RCA output jacks.
- Line level (0db) output level.
- 3 position terminal blocks for microphone connections.
- Separate volume control for each microphone.
Master volume control
- LED power indicator.
- Power: 12 VDC @ 50mA
- Reverse polarity protected.
- PPTC fused.
- Black plastic ABS housing.
- Dimensions: L 4.3 x W 2.7 x H 1.6
- Weight .12kg

Caution

It is the responsibility of the installation company and end user to comply with state and federal privacy laws regarding the use of audio surveillance equipment. If you are unfamiliar with these laws, consult a qualified attorney. In most cases, posting the provided warning labels in plain view is all that is required.

Warranty : 1 year parts and labor.

Made in USA