

ETS

Electronic Technical Services Inc.
211 Conchas SE
Albuquerque, NM 87123
PH 505-888-3923 FAX 505-888-3926
Website: www.etsnm.com

HSM11-C5 Outdoor Speaker / Microphone

Description

Weather resistant Omni-directional pre-amplified microphone and 7x11 inch horn speaker for use in two way public address audio surveillance systems and ONLY with one of our -C5 Interface products to make fast and clean connections to DVRs, I/P cameras, etc. Single CAT5 cable connects the HSM11-C5 to a compatible interface, typically located near the DVR or I/P camera. An extra set of wires available in the CAT5 cable is broken out on quick connect terminals of the HSM11-C5 for connecting a remote call switch, door release relay or alarm contact.

Includes

- 1ea HSM11-C5 Speaker/microphone.
- Installation instructions.

Wiring Requirements

- 1ea. CAT5 cable:
300' max. @30W
1000' max @10W

Caution

It is the responsibility of the installation company and end user to comply with state and federal privacy laws regarding the use of audio surveillance equipment. If you are unfamiliar with these laws, consult a qualified attorney. In most cases, posting the provided warning label in plain view is all that is required.



HSM11-C5 Microphone / Speaker

- 7x11" horn speaker with swivel mount.
- Omni-directional 25' pickup pattern.
- Low noise MOSFET pre-amplifier.
- 200Hz-16Khz Frequency response. Significantly reduces background noise.
- Removable .5" windscreen
- Adjustable gain.
- Microphone audio peak limiter (1second attack/release response time).
- Power: 12VDC @ 10mA.
- On-board voltage regulator and RFI filtering.
- 600 Ohm balanced audio output transformer.
- 70v line audio input 4, 8, 16, 32 Watt switch selectable 70v transformer taps
- 400Hz-10Khz speaker frequency response.
- RJ45 jack for single field cable run.
- Call switch output terminal block.
- Dimensions: 7x11 horn x L11.5.

Warranty

1 year parts and labor.

Made in USA