



Electronic Technical Services Inc.
211 Conchas SE
Albuquerque, NM 87123
PH 505-888-3923 FAX 505-888-3926

Sound Surveillance™

SM2 DVR / IP Camera Microphone Interface Adapter

Description

Powers an SM1 series microphone and routes its audio output to an RCA jack (or 3.5mm) for connection to equipment with a un-balanced line level input. Ideal for DRVs, remote monitoring applications, and CCTV monitors with built in speakers.



Includes

- SM2 Interface adapter.
- 12 VDC AC adapter.
- 1 each 3' RCA or 3.5mm patch cable (please specify).
- Installation instructions.

Options

- SPECIFY: RCA OR 3.5mm output connector.

Wiring Requirements

- Microphone cable run: Stranded 22-gauge, 2-conductor shielded cable. Distances up to 1500 feet.

Warranty : 1 year parts and labor.

Made in USA

SM2 Interface Adapter Specifications

- Standard RCA or 3.5mm jack for connection to DVRs etc.
- Line level (0db) output level.
- Euro-style connector makes cable termination fast and clean.
- LED power indicator.
- Power: 12 VDC @ 10mA
- Reverse polarity protected.
- All power circuitry and cable run protected with auto-reset type fuse.
- Black plastic ABS housing.
- Dimensions: L 2.7 x W 1.7 x H 1.6

Caution

It is the responsibility of the installation company and end user to comply with state and federal privacy laws regarding the use of audio surveillance equipment. If you are unfamiliar with these laws, consult a qualified attorney. In most cases, posting the provided warning labels in plain view is all that is required.