



Electronic Technical Services Inc.
211 Conchas SE
Albuquerque, NM 87123
PH 505-888-3923 FAX 505-888-3926
Website: www.etsnm.com

Sound Surveillance™

MPI-1 Microphone Pre-amplifier

Description

The MPI-1 is a microphone pre-amplifier designed to be used with any of our ML1 series microphones. MPI-1 features adjustable lo cut filter and gain controls. The output of the MPI-1 is designed to be connected to directly to DVRs, Audio recorders, etc.



Includes:

- MPI-1 Pre-amplifier
- 15Vdc AC adapter
- 6' audio patch cord
- Installation instructions.

Option (add to P/N):

- 3.5mm for 3.5mm ended patch cord
- RCA for RCA ended patch cord
- FL for flying lead ended patch cord

Caution

It is the responsibility of the installation company and end user to install this audio surveillance equipment in compliance with state and federal privacy laws. If you are unfamiliar with these laws, consult a qualified attorney.

MPI-1 Specifications

- Low noise MOSFET pre-amplifier.
- 200Hz-13Khz Frequency response.
- Adjustable lo cut filter 200-1khz can significantly reduce background noise.
- Jumper selectable volume range:
"Line level" (0db) or
"Microphone level" (-30db)
- Adjustable gain in both volume ranges.
- 100 Ohm unbalanced output.
- Internal peak limiter circuit (.5 sec response)
- Power: 12-24vdc @ 10mA.
- Fused and polarity protected power input
- 2.1mm x 5.5mm barrel power in tip -
- On-board voltage regulator and RFI filtering.
- Temperature range -25C to 85C.
- Black plastic ABS housing.
- Dimensions: L 2.7 x W 1.7 x H 1.6
- Weight .05lbs

Warranty

1 year parts and labor.

Made in USA