



Electronic Technical Services Inc.
211 Conchas SE
Albuquerque, NM 87123
PH 505-888-3923 FAX 505-888-3926
Website: www.etsnm.com

Sound Surveillance tm

SMI-1 Microphone Interface Adapter

Description

Powers an SM1 series microphone and routes its audio output to an RCA jack for connection to equipment with a un-balanced line level input. Ideal for DRVs, remote monitoring applications, and CCTV monitors with built in speakers.



Includes

- SMI-1 Interface adapter.
- 15 VDC 800ma AC adapter.
- 1 each 6' RCA patch cord
- Installation instructions.

Options:

- Add -RCA or -FL (Flying Leads) to P/N for alternate output cables.

Wiring Requirements

- Microphone cable run: Stranded 22-gauge, 2-conductor shielded cable. Distances up to 1000 feet.

SMI-1 Interface Adapter Specifications

- RCA output jack.
- Line level (0db) output level.
- 3 position terminal block microphone connection
- LED power indicator.
- Power: 12 VDC @ 10mA
- Reverse polarity protected.
- PPTC fused.
- Black plastic ABS housing.
- Dimensions: L 2.7 x W 1.7 x H 1.6
- Weight .05kg

Caution

It is the responsibility of the installation company and end user to comply with state and federal privacy laws regarding the use of audio surveillance equipment. If you are unfamiliar with these laws, consult a qualified attorney. In most cases, posting the provided warning labels in plain view is all that is required.

Warranty : 1 year parts and labor.

Made in USA