



Electronic Technical Services Inc.
211 Conchas SE
Albuquerque, NM 87123
PH 505-888-3923 FAX 505-888-3926
Website: www.etsnm.com

Sound Surveillance™

SMI-1L Microphone Interface Adapter with Volume Control

Description

Powers an SM1 series microphone and routes its audio output to an RCA jack (or 3.5mm) for connection to equipment with a un-balanced line level input. For use with DRVs, IP cameras, remote monitoring applications, and CCTV monitors with built in speakers. Ideal for use with any SM1-X microphone and IP camera "microphone level" inputs.



Includes

- SMI-1L Interface adapter.
- 15 VDC 800ma AC adapter.
- 1 each 3' RCA or 3.5mm patch cable.
- Installation instructions.

Options:

- Add -RCA or -FL (Flying Leads) to P/N for alternate output cables.

Wiring Requirements

- Microphone cable run: Stranded 22-gauge, 2-conductor shielded cable. Distances up to 1000 feet.

Warranty : 1 year parts and labor.

Made in USA

SMI-1L Interface Adapter Specifications

- RCA connector
- 3 position terminal block microphone connection.
- Adjustable audio output level control.
- Power: 12VDC @ 10ma.
- Reverse polarity protected
- PPTC fused.
- Dimensions: L 2.7 x W 1.7 x H 1.6
- Weight .05kg

Caution

It is the responsibility of the installation company and end user to comply with state and federal privacy laws regarding the use of audio surveillance equipment. If you are unfamiliar with these laws, consult a qualified attorney. In most cases, posting the provided warning labels in plain view is all that is required.