



Electronic Technical Services Inc.  
211 Conchas SE  
Albuquerque, NM 87123  
PH 505-888-3923 FAX 505-888-3926  
Website: www.etsnm.com

Sound Surveillance™

## SM8 8 Channel listen only mixer / switcher

### Description

Stand alone 8 channel base station for monitoring 8 SM1 series microphones. Terminals for connecting and powering up to 8 Sound Surveillance SM1 series microphones. Two modes of operation: Select one of 4 mode or mix in / out any combination mode. Connects to DVRs or audio recorders for live monitoring or playback Headphone jack for private listening.



### Includes

- SM8 mixer / switcher base station
- 2 RCA patch cords
- 15VDC AC adapter.
- Installation instructions

### Microphone wiring Requirements

- Stranded 22-gauge, 2-conductor shielded cable with drain wire.  
Max. cable length: 1000'.

### Caution

*It is the responsibility of the installation company and end user to comply with state and federal privacy laws regarding the use of audio surveillance equipment. If you are unfamiliar with these laws, consult a qualified attorney. In most cases, posting the provided warning label in plain view is all that is required.*

### SM8 Specifications

- 2 Watt speaker power amplifier
- 3" full range speaker
- 3.5mm headphone jack
- Line level input and output jacks for connection to DVRs and audio recorders.
- Recorder monitor switch.
- Level controls for each microphone.
- In / out switch for each microphone.
- Two modes of operation: Select one of 8 mode or mix in / out any combination mode.
- Master volume control
- Power: 12-15Vdc @ 300ma
- Reverse polarity protected and fused.
- High quality metal enclosure
- Dimensions: L7.90 x W7.10 x H 1.25
- Weight : .75Kg

### Warranty

1 year parts and labor.

Made in U.S.A.