



Electronic Technical Services Inc.
211 Conchas SE
Albuquerque, NM 87123
PH 505-888-3923 FAX 505-888-3926

Sound Surveillance™

STW2 Single Zone Listen / Talk Back Monitoring Station

Description

Stand alone single zone, two way, listen and talk back monitoring station. Terminals for connecting a STW1 and STW1-SE speaker / microphone. DVR / recorder in out function permits recording and playback of both sides of conversations. Built in microphone with push to talk function.



Includes

- STW2 base station
- 2 RCA patch cords
- 12Vdc AC adapter.
- Installation instructions

Microphone / speaker wiring Requirements

- 2 each, Stranded 22-gauge, 2-conductor shielded cable with drain wire. Max. cable length: 500'.

Caution

It is the responsibility of the installation company and end user to comply with state and federal privacy laws regarding the use of audio surveillance equipment. If you are unfamiliar with these laws, consult a qualified attorney. In most cases, posting the provided warning label in plain view is all that is required.

STW2 Specifications

- 2 Watt speaker power amplifier
- 3" full range speaker
- 3.5mm headphone jack
- Line level input and output jacks for connection to DVRs and audio recorders.
- Recorder monitor switch.
- Page tone for microphone / speaker equipped with call switches.
- Remote speaker volume control.
- 2 Watt 70v line speaker drive signal.
- Push to talk momentary switch
- Built in talk back microphone.
- Master volume control
- Power: 12-15Vdc @ 250ma
- Reverse polarity protected and fused.
- High quality metal enclosure
- Dimensions: L5.50 x W4.10 x H 1.60.
- Weight .4Kg

Warranty

1 year parts and labor.

Made in U.S.A.