

**Electronic Technical Services Inc.**  
211 Conchas SE  
Albuquerque, NM 87123  
PH 505-888-3923 FAX 505-888-3926  
Website: www.etsnm.com

## SMA1-HPC5 Speaker Driver Microphone Interface

### Description

The SMA1-HPC5 is a line level, 30 Watt, 70V speaker driver (power amplifier) and SM series microphone interface typically for use in 2 way audio surveillance systems. A single CAT5 cable connects the SMA1-HPC5 to any ETS speaker/microphone ordered with a C5 option. Directly connects to DVRs and remote monitoring equipment.

Use one of our Sound Surveillance speakers with a built in 70V transformer & SM1 microphone (CAT5 option) for cable runs up to 350 feet.

### Includes

- SMA1-HPC5 Speaker driver / microphone interface.
- 24 VAC 50VA AC adapter.
- 2 each 6' RCA or 3.5mm patch cable.
- Installation instructions.

### Options

- SPECIFY: RCA or 3.5mm input connectors.

### Wiring Requirements

- 1 CAT5 8 conductor cable and 2 each RJ45 connectors. 350' max.

Warranty : 1 year parts and labor.

Made in USA



### SMA1-HPC5 Speaker/Mic. interface

- Single CAT5 cable run up to 350' between SMA1-HPC5 and speaker/microphone. Line level (0db) audio input and outputs.
- Standard RCA or 3.5mm jacks for connection to DVRs etc.
- Adjustable independent volume controls for speaker and microphone.
- 30 Watts RMS power output (70v balanced line).
- Balanced 600 Ohm microphone signal transmission. Audio is transformer converted to unbalanced.
- Frequency response 200-10Khz.
- Short circuit protected.
- Built in 70V 30w audio power transformer.
- Euro-style connectors makes speaker and microphone cable terminations fast and clean.
- LED power indicator and Auto reset fused.
- Call sw: unreferenced, 2 free terminals.
- Power:24 VAC @ 2000mA
- Grey plastic ABS housing.
- Dimensions: L 5.3 x W 3.3 x H 1.6

### Caution

It is the responsibility of the installation company and end user to comply with state and federal privacy laws regarding the use of audio surveillance equipment. If you are unfamiliar with these laws, consult a qualified attorney. In most cases, posting the provided warning labels in plain