

Electronic Technical Services Inc. 211 Conchas SE Albuquerque, NM 87123 PH 505-888-3923 FAX 505-888-3926 Website: www.etsnm.com

CAT5-AD1 Channel Cabling Adaptor

Description

The CAT5-AD1 adaptor set is used to power up and transmit the audio signal from any ETS SM1 series microphone over CAT5/6 cable. Compatible with all ETS interface boxes and base stations



Includes

- 2ea CAT5-AD1 board
- Installation instructions

Wiring requirements:

- Microphone and interface to CAT5-AD1 boards 2 conductor shielded #22, 100 feet max
- CAT5 cable run 1000 feet max

CAT5-AD1 Features and Specifications

- RJ45 (8 conductor) female connector blocks.
- 3 position terminal blocks for microphone and interface connections.
- Converts SM1 series microphone signals to balanced audio at 10K Ohms impedance permitting the use of long distance CAT5 unshielded cable runs.
- Double stick tape mounting.
- Dimensions: L2.1 x W.94 x H.94
- Weight: .02kg

Warranty 1 year parts and labor.

Made in USA