



Sound Surveillance™

Electronic Technical Services Inc.  
211 Conchas SE  
Albuquerque, NM 87123  
PH 505-888-3923 FAX 505-888-3926  
Website: www.etsnm.com

# SA4 Four Channel 70V / 8 Ohm Speaker Driver

## Description

The SA4 is a 4 channel, line level in to 2 Watt, selectable 70V or 8 Ohm speaker driver (power amplifier) typically for use in 2 way audio surveillance systems. Directly connects to DVRs and remote monitoring equipment. The SA1 can also be used in any four zone public address application. Use our Sound Surveillance speakers with a built in 70V transformers to permit speaker cable runs up to 1000 feet.



## Includes

- SA4 Speaker driver.
- 16 VAC 20VA AC adapter.
- 4 each 3' RCA or 3.5mm patch cables.
- Installation instructions.

## Options

- SPECIFY: RCA OR 3.5mm input connectors.

## Wiring Requirements

- Speaker cable runs: stranded 22-gauge, 2-conductor:
- 70V mode: 1000 feet max each run.
- 8 Ohm mode: 100 feet max each run.

Warranty : 1 year parts and labor. Made in USA

## SA4 Speaker Driver Specifications

- Line level (0db) audio inputs.
- Standard RCA or 3.5mm jacks for connection to DVRs etc.
- Adjustable Volume controls.
- Selectable 70V or 8 Ohm output levels.
- 2 Watts RMS power output @ 200-10Khz.
- Euro-style connectors makes speaker cable terminations fast and clean.
- LED power indicator.
- Power:16 VAC @ 500mA
- Reverse polarity protected.
- Auto reset fused.
- Black plastic ABS housing.
- Dimensions: L 4.2 x W 2.7 x H 1.6

### Caution

It is the responsibility of the installation company and end user to comply with state and federal privacy laws regarding the use of audio surveillance equipment. If you are unfamiliar with these laws, consult a qualified attorney. In most cases, posting the provided warning labels in plain view is all that is required.