



Fire Sets Stay Behind-M

Electronic Technical Services Inc.
211 Conchas SE
Albuquerque, NM 87123
PH 505-888-3923 FAX 505-888-3926
Website: www.etsnm.com

Description

The Fire Set-M series are field deployable devices that are used to capture personnel movement in military training exercises and security applications. The Stay Behind-M is a stand alone, motion detector based alarm system.



Stay Behind-M Functions

- Can only be locally armed and disarmed.
- Exit delay timer: adjustable 2-60 seconds delay.
- Alarm timer: adjustable 2-60 seconds delay or "on" until disarmed or powered down.
- Built-in 30 feet by 45 degree PIR type motion detector.
- Loud internal 100db, 2 tone Piezo sounder and yellow alarm strobe
- Thumb screw / banana terminals for connecting pyrotechnics or large strobes and sirens.

Includes

- Stay Behind-M
- AC charger / adaptor

Warranty

1 year parts and labor.

Made in USA

Stay Behind-M Specifications

- Heavy duty, cast aluminum housing and other components.
- High quality switches with safety ring prevents accidental activation and can be pressed easily, even while wearing gloves.
- Internal, high capacity 2.45A/Hr NiMH Rechargeable battery pack. 8 hour operation time on a full charge.
- Selectable: internal PIR sensitivity pulse count setting of 2 or 4 counts.
- 12Vdc output @ 1Amp Max. for driving larger strobes, sirens and pyrotechnics.
- LED power on, alarm, motion and charging indicators.
- All LEDs are bright enough to be seen in broad daylight.
- Charging jack: 5.5mm x 2.1mm
- Charging current: 12Vdc in @ 100ma
- Dimensions (body) L:4.7 x W 4.7 x H 2.3