



Electronic Technical Services Inc.
211 Conchas SE
Albuquerque, NM 87123
PH 505-888-3923 FAX 505-888-3926
Website: www.etsnm.com

Sound Surveillance™

SMEQ-1 Seven Band Equalizer and DVR, IP Camera Microphone Interface

Description

The SMEQ-1 is a 7 band audio equalizer and DVR, IP camera interface designed to be used with ETS SM1 series microphones. The SMEQ-1 can also be connected in between a SM1 series microphone and any ETS base station. Provides +/-12db sound emphasis or de-emphasis of 7 ranges of frequencies (60hz-15khz) for acoustically difficult environments such as interrogation / interview rooms. The user can tune out unwanted background noise and emphasize the desired sound source.



Includes

- SMEQ-1 Equalizer / interface
- 12 VDC AC adapter.
- 1 each 3' RCA or 3.5mm patch cables.
- Installation instructions.

Options

- SPECIFY: RCA OR 3.5mm input / output connectors.

Wiring Requirements

- Microphone cable run: Stranded 22-gauge, 2-conductor shielded cable. Distances up to 1500 feet.

SMEQ-1 Specifications

- Connect any ETS SM1 series microphone directly to the SMEQ-1.
- Includes RCA (or specify 3.5mm) patch cable and 12Vdc AC adaptor.
- 7 frequency band controls: 60hz, 150hz, 400hz, 1Khz, 2.5Khz, 6Khz, 15Khz.
- +/- 12db gain / cut for each frequency band.
- Line level RCA input / output jacks and 3 terminal connectors for connections to ETS microphones, base stations or IP cameras.
- Output level control.
- Reverse polarity protected and fused.
- Black ABS enclosure.
- Dimensions: L 5.3 x W 3.3 x H 2.3

Warranty : 1 year parts and labor.

Made in USA